

AV008 8 Cell Lithium Iron Phosphate Experimental Battery with balance charging port

<p>Dimensions (Metric): 114MM (L) x 61MM (W) x 112MM (H) Dimensions (Standard): 4.5" (L) x 2.5" (W) x 4.25" (H) Negative Terminal Location: Right Weight: 768 grams (1.7 lb) Voltage (Charged): 13.6V Lead Acid Equivalent Amperage: 15 A/H @ 10 A/H Rating Pulse Cranking Amps: 275 CCA Operating Environment: -18°C (0°F) to 60°C (140°F)</p>	<p>Applications for 100 amp to 200 amp starter draw</p> <ul style="list-style-type: none"> • Rotax twin cylinder two strokes up to 600cc • Hirth twin cylinder two strokes up to the 3503 70HP Series • HKS-700E series two cylinder four stroke engines
--	--



AV012 12 Cell Lithium Iron Phosphate Experimental Battery with balance charging port

<p>Dimensions (Metric): 114mm (L) x 87mm (W) x 112m (H) Dimensions (Standard): 4.5" (L) x 3.5" (W) x 4.25" (H) 12 Cell EVO2 Negative Terminal Location: Right 12 Cell EVO2 L Negative Terminal Location: Left Weight: 1106 grams (2.44 lbs.) Voltage (Charged): 13.6V Lead Acid Equivalent Amperage: 20 A/H @ 10 A/H Rating Pulse Cranking Amps: 410 amps Operating Environment: -18°C (0°F) to 60°C (140°F)</p>	<p>Applications for 200 amp to 300 amp draw</p> <ul style="list-style-type: none"> • Jabiru 2200 and 3200 series engines • Rotax 912 and 914 series engines • Lycoming Low Compression 4 cylinders • Continental Low Compression 4 cylinders
--	---




AV016 16 Cell Lithium Iron Phosphate Experimental Battery with balance charge port


<p>Dimensions (Metric): 114mm (L) x 114mm (W) x 112mm (H) Dimensions (Standard): 4.5" (L) x 4.5" (W) x 4.25" (H) Negative Terminal Location: Left Weight: 1611 grams (3.5 lbs.) Voltage (Charged): 13.6V Amperage: 9.2Amp/Hour Lead Acid Equivalent Amperage: 28 A/H @ 10 A/H Rating Pulse Cranking Amps: 500 amps Operating Environment: -18°C (0°F) to 60°C (140°F)</p>	<p>Applications for 300 amp to 500 amp draw</p> <ul style="list-style-type: none"> • Jabiru 2200 and 3200 series engines • Rotax 912 and 914 series engines • VW and Corvair Engines • Lycoming IO 360 200 HP series
---	---



AVVAULT Aerovoltz Battery Vault holds up to the AV016 battery. Mounts on the bottom or back. All holes predrilled comes assembled



AVVAULTLW Aerovoltz Light Weight Battery Box. Fits up to AV016 battery. Comes assembled and drilled.



AVC-110 110V Lithium Battery Balance Charger

AVC-220 220-240V Balance Charger

Chargers are pre-programmed and ready for use. Will also charge other forms of batteries from various forms of Lithium, NiCad, PB, and more.

Built-in power supply, balance charging cable, and terminal leads with clips.



Aerovoltz Batteries
3003 Campfire Court , Jamestown NC
Contact: Steve Johnson 336-688-4784
sjohnson@everythingaero.net www.aerovoltz.net