

Single Color & Dual Color Light Strip Wiring Instructions

Single Color Strip: Colored Wire is DC (+), Black wire is Ground (-)

Dual Color Strip: Colored Wire is DC (+), White wire (or wire with white stripe) is White LED DC (+). Black wire is common Ground (-).

For best results with PWM dimmers, directly wire both the (+) & (-) leads from the light strip to the dimmer outputs. Chassis ground is not recommended.

LED Light strips are trimmable.

Check the images here to determine which model or production series of strip you have.

Cut marks appear about every 2.5 to 3", depending on the specific LED strip



Cut on the white line that runs underneath the solder dots



Cut on the "Scissor" icon



Cut Between The 2 Rows of Dots